

Fonction	Ecriture	Symbole UE	Symbole US	Table de vérité	Diagramme de Venn	Schéma	Logigramme															
Oui	$S = x$			<table border="1"> <tr><td>x</td><td>S</td></tr> <tr><td>0</td><td>0</td></tr> <tr><td>1</td><td>1</td></tr> </table>	x	S	0	0	1	1												
x	S																					
0	0																					
1	1																					
Non Pas Inverse	$S = \bar{x}$ $S = \neg x$			<table border="1"> <tr><td>y</td><td>S</td></tr> <tr><td>0</td><td>1</td></tr> <tr><td>1</td><td>0</td></tr> </table>	y	S	0	1	1	0												
y	S																					
0	1																					
1	0																					
Disjonction ou	$S = x + y$ $S = x \vee y$			<table border="1"> <tr><td>x</td><td>y</td><td>S</td></tr> <tr><td>0</td><td>0</td><td>0</td></tr> <tr><td>0</td><td>1</td><td>1</td></tr> <tr><td>1</td><td>0</td><td>1</td></tr> <tr><td>1</td><td>1</td><td>1</td></tr> </table>	x	y	S	0	0	0	0	1	1	1	0	1	1	1	1			
x	y	S																				
0	0	0																				
0	1	1																				
1	0	1																				
1	1	1																				
Conjonction et	$S = x \cdot y$ $S = x \wedge y$			<table border="1"> <tr><td>x</td><td>y</td><td>S</td></tr> <tr><td>0</td><td>0</td><td>0</td></tr> <tr><td>0</td><td>1</td><td>0</td></tr> <tr><td>1</td><td>0</td><td>0</td></tr> <tr><td>1</td><td>1</td><td>1</td></tr> </table>	x	y	S	0	0	0	0	1	0	1	0	0	1	1	1			
x	y	S																				
0	0	0																				
0	1	0																				
1	0	0																				
1	1	1																				
Non et	$S = \overline{x \cdot y}$ $S = \neg x \wedge y$			<table border="1"> <tr><td>x</td><td>y</td><td>S</td></tr> <tr><td>0</td><td>0</td><td>1</td></tr> <tr><td>0</td><td>1</td><td>1</td></tr> <tr><td>1</td><td>0</td><td>1</td></tr> <tr><td>1</td><td>1</td><td>0</td></tr> </table>	x	y	S	0	0	1	0	1	1	1	0	1	1	1	0			
x	y	S																				
0	0	1																				
0	1	1																				
1	0	1																				
1	1	0																				
Non ou	$S = \overline{x + y}$ $S = \neg x \vee y$			<table border="1"> <tr><td>x</td><td>y</td><td>S</td></tr> <tr><td>0</td><td>0</td><td>1</td></tr> <tr><td>0</td><td>1</td><td>0</td></tr> <tr><td>1</td><td>0</td><td>0</td></tr> <tr><td>1</td><td>1</td><td>0</td></tr> </table>	x	y	S	0	0	1	0	1	0	1	0	0	1	1	0			
x	y	S																				
0	0	1																				
0	1	0																				
1	0	0																				
1	1	0																				
ou exclusif	$S = x \oplus y$			<table border="1"> <tr><td>x</td><td>y</td><td>S</td></tr> <tr><td>0</td><td>0</td><td>0</td></tr> <tr><td>0</td><td>1</td><td>1</td></tr> <tr><td>1</td><td>0</td><td>1</td></tr> <tr><td>1</td><td>1</td><td>0</td></tr> </table>	x	y	S	0	0	0	0	1	1	1	0	1	1	1	0			
x	y	S																				
0	0	0																				
0	1	1																				
1	0	1																				
1	1	0																				